

SYNCRO 800-2000VA

Uninterruptible Power Supply

Minimum consumption

Syncro is a range of UPS systems with LINE INTERACTIVE technology, providing a reduction in energy consumption and 99% efficiency.

Voltage stability

Syncro's automatic voltage regulator (AVR) is able, for mains voltage variations not exceeding + 20% / - 25%, to stabilize the output voltage at values between -15% / +17% with respect to the nominal voltage. For voltage variations greater than +20% / -25%, the unit powers the load from the battery via the inverter, providing an output voltage stabilized at $\pm 5\%$.

Timer for programmed shutdown (via software)

This feature allows fully automatic programmed and timed start-ups and shutdowns.

Automatic restart

The UPS is programmed to restart automatically when the mains power supply returns after switching off due to the end of back-up time following an extended mains power failure.

Total microprocessor control

Digital control considerably improves the reliability of the UPS, reduces unit dimensions and weight, and significantly increases control and communications capabilities.

Battery optimization

The UPS periodically and automatically performs a battery efficiency test. The batteries are recharged by means of a rapid charge battery charger. The UPS is thus always guaranteed maximum back-up time. The Syncro range also comes with a device to protect against deep discharges, which can significantly reduce the expected life of the batteries.

Reduced noise

Through the use of high frequency components and fan speed control, the noise level of the UPS is kept under 40 dBA.

Advanced communication

The Aros Watch&Save 3000 software ensures effective and intuitive management of the UPS. Important information such as the input and output voltage, the load applied, the remaining back-up time, etc., is displayed in the form of bar graphs. The software is able to provide information even in the event of a failure, and can also programme the UPS for automatic weekly start-up and shutdown.

Protection of the telephone line

Syncro comes with a RJ45/RJ11 telephone socket to guarantee the protection of its telephone line/modem against any overvoltages.

Applications

Personal computers, small/medium



computer networks.

SYNCRO 800-2000VA

Uninterruptible Power Supply

INPUT	SYNCRO 800	SYNCRO 1000	SYNCRO 1500	SYNCRO 2000
Voltage	230 V			
Voltage tolerance	+20%/-25%			
Input frequency	50/60 Hz			
Accepted frequency	±5%			
Input phases	1			
BATTERIES	SYNCRO 800	SYNCRO 1000	SYNCRO 1500	SYNCRO 2000
Type	Maintenance-free sealed lead-acid			
Battery blocks	12V/7Ah		12V/9Ah	
Batteries number	2			3
Recharge time	6-8 h			
OUTPUT	SYNCRO 800	SYNCRO 1000	SYNCRO 1500	SYNCRO 2000
Rated power	800 VA	1000 VA	1500 VA	2000 VA
Active power	480 W	600 W	900 W	1200 W
Phases number	1			
Waveform	Step-wave			
Rated voltage (on battery operation)	230 V ±5%			
Rated voltage (on mains operation)	The AVR circuit regulates the output voltage from +17% to -15% with input variation of ±25%			
Frequency on battery operation	50 or 60 Hz (+/- 0.5%)			
Output phases	1			
Output sockets	No. 4 IEC 320 (10A)			
SYSTEM	SYNCRO 800	SYNCRO 1000	SYNCRO 1500	SYNCRO 2000
Transfer time	2 ms typical, 4 ms max.			
AC/AC efficiency	99%			
Noise	< 40 dBA at 1 mt			
Operating temperature	0°C / +40°C, optimal for batteries +15°C/+25°C			
Relative humidity	< 95% non condensing			
Approvals	CE, GS/TÜV	CE, GS/TUV		
Protections	Overcurrent - short-circuit - excessive battery discharge			
Net/telephone line protection	RJ45/RJ11 filtered socket			
Communication	RS232 port			
Colour	Dark grey			
Standards	Sicherheit: EN 62040-1-1 und Richtlinie 2006/95/EC; EMV: EN 62040-2 and directive 2004/108/EC			
Technology	Line Interactive			
Weight (kg)	14 Kg		15 Kg	20 Kg
Dimensions (WxDxH) mm	140x375x180 mm			140x410x214 mm
DATA	SYNCRO 800	SYNCRO 1000	SYNCRO 1500	SYNCRO 2000
Back up time at full load (min)	5 Min.	6 Min.		
Installation	Tower			
Configuration	Single Unit			
OPTIONS	SYNCRO 800	SYNCRO 1000	SYNCRO 1500	SYNCRO 2000
Communication software 'professional' version	Yes			

SYNCRO 800-2000VA

OPTIONS	SYNCRO 800	SYNCRO 1000	SYNCRO 1500	SYNCRO 2000
MultiCom 351	X	X	X	X
MultiCom 301	X	X	X	X
NetMan 101 Plus	X	X	X	X
USB converter	X	X	X	X
Multi I/O	X	X	X	X
IRMS Multi-Switch	X	X	X	X
AS/400 interface kit	X	X	X	X
External by-pass cabinet rack 16A	X	X	X	X
MultiCom 401	X	X	X	X